



skytec 172.572

STL6A 6-Channel Mixer with Amplifier SD/USB/MP3/DSP

This 6-channel mixer holds a 2x 300W amplifier. Giving the user a complete unit as base for this setup. With 4 microphone and line inputs it's ideal for live performers on stage. 16 digital effects give you plenty of room to fine tune your sound.

Output power: 4 Ohms	2x 300W
Output power: 8 Ohms	2x 240W
Frequency response	20Hz - 20kHz
THD	
Equalizer	5 Band (\pm 12dB)
Equalizer: High	\pm 15dB / 12kHz
Equalizer: Low	\pm 15dB / 80Hz
Input:Line	+5dB ~ -40dB
Input:Mic	-15dB ~ -60dB
Output level	+12dB (3V)
Output:Record	0dB (775mV)
Headphone output	300mW @ 32 Ohm
Signal to noise ratio	>90dB
Power supply	220~240Vac / 50Hz
Dimensions	315 x 296 x 132mm
Weight	5.9kg

- 2x 300W power amplifier
- MP3 player with USB port and SD slot
- +48V phantom power
- Stereo 5-band equalizer
- 16 digital effects (DSP)
- PFL per channel
- RCA line input
- Tone control per channel
- 6.3mm outputs (L+R)