



PD Power Dynamics 172.612
Professional Audio

PDM-M604A 6-Channel Music Mixer with Amplifier

Table top design music mixer with built-in amplifier and many attractive features. Features include mute and solo switches on every channel, built-in USB player with digital display and BT receiver to stream music to the mixer during the break. Ideal for live setups and small bands.

Power Continue	2x 200W rms
Output power	400W
Frequency response	10Hz -45kHz (± 3 dB)
THD	
DSP Resolution	24-bit
Type of effects	Hall, Room, Reverb delay, Delay, Echo, Ping pong delay
Presets	16
Signal to noise ratio	>112dB
Output level	+/- 1V
Input:Line	+/- 150mV
Input: Mic	+/- 1.5mV
Power supply	220-240VAC / 50-60Hz
Dimensions	350 x 370 x 125mm
Weight	7.3kg

- 6 Balanced mono microphone-/line input (Combi XLR/Jack)
- +48V phantom power with individual preamp per channel
- Stereo line input (RCA)
- Multi-FX processor with 16 presets
- Solo switch per channel (PFL)
- On/off switch per channel
- Hi, Mid and Low control for each channel
- Adjustable FX volume per channel
- Adjustable Pan per channel
- Stereo balanced main outputs (XLR)
- Separate headphones and stereo rec outputs
- 7-Band equalizer
- Built-in 2x 200W RMS Amplifier
- Built-in USB player with digital display
- BT-receiver for audio streaming
- LED VU meter and Peak LED's