



PDM-S804A 8-Channel Stage Mixer with Amplifier

Table top design stage mixer with built-in amplifier and many attractive features. Features include mute and solo switches on every channel, built-in USB player with digital display and BT receiver.

Power Continue	2x 350W rms
Output power	700W
Frequency response	10Hz -45kHz (± 3 dB)
THD	
DSP Resolution	24-bit
Type of effects	Early ref, Chorus, Phaser, Flanger, Symphonic, Doubler, Radio voice, Distortion, Delay, room, Chapel, Hall, Plate, Gated, Reverse, Ambience, Pitch shift, Ping pong delay
Presets	2x 99
Output level	+/- 1V
Input:Line	+/- 150mV
Input: Mic	+/- 1.5mV
Power supply	220-240VAC / 50-60Hz
Dimensions	425 x 415 x 166mm
Weight	12kg

- 4 Balanced mono microphone-/line input (Combi XLR/Jack)
- 2 Balanced stereo line inputs (6.3mm Jack)
- 2 Balanced stereo line inputs (RCA)
- +48V phantom power with individual preamp per channel
- 75Hz Low cut filter per channel
- Adjustable FX, Pan, Trim per channel
- Aux send per channel
- Solo switch per channel (PFL)
- Mute switch per channel
- Dual Multi-FX processor with both 99 presets
- Built-in 2x 350W RMS Amplifier
- Stereo balanced main outputs (XLR + 6.3mm Jack)
- 9-Band Equalizer
- Separate control room and headphones outputs
- Built-in USB player with digital display
- BT-receiver for audio streaming
- LED VU meter and Peak LED's