



172.652 **PD** Power Dynamics
Professional Audio

PDM-X601 6-Channel Studio Music Mixer

The PDM-X Mixer series consist of multipurpose music mixers with USB port allowing you to directly connect a USB stick with MP3 files to the MP3 player. All information can be seen on the clear LCD display, with ID3 tag readout. The PDM-X mixers are also equipped with a BT receiver so you can stream music directly from your smartphone or other BT enabled device. For a reliable power source, the PDM-X mixers have +48V phantom power and come with an external power adapter. Ideal for studio use, audio recording, live performances, karaoke and many more.

Playback options : BT streaming, USB
Input connections : 6.3mm Jack, USB, XLR (3-pin)
Output connections : 6.3mm Jack, XLR (3-pin)
Output channels : 2
Frequency response : 20Hz - 20.000Hz
THD :
Equalizer : 2-Bands
Equalizer: Low : 80Hz +15dB
Equalizer: High : 12KHz +15dB
Output level: Master : 3V
Power supply : 100-240VAC 50/60Hz (5V Adapter)
Dimensions (L x W x H) : 170 x 220 x 65mm
Weight : 1,20

- 6-channel digital studio music mixer
- 4x combined Jack/XLR inputs with +48V phantom power
- Integrated USB MP3 player
- Built-in BT receiver allows music streaming from mobile devices
- 1 stereo line input (6.3mm Jack)
- 2x stereo balanced main outputs (XLR)
- Separate control room and headphones outputs
- Hi and low control per channel
- FX send/return
- LCD display with ID3 tag readout: Display Song Title / Artist
- Peak LED each mono channel