



MAX 7017 - 5-Channel USB / MP3 Mixer -

The NEW MAX 7017 Clubmixer is a totally new design. Some great features have been added but the real work has been done on improving the quality and performance, making it the best value mixer on the market.

- * 5 Channel 19inch / 6U / 17 Input DJ Mixer
- * 1 Dedicated balanced Mic channel with 2-band EQ
- * 2 Auxiliary Mics on channels 2 and 3
- * 2 Phono inputs switchable to line level inputs
- * 8 CD / Line inputs plus 4 switchable
- * 3.5mm Aux input on top panel for external sound sources such as an MP3 player
- * 2 USB Input / Outputs on channels 3 and 4
- * Fully assignable VCA crossfader
- * Hotswap channel faders allow changing in seconds
- * Individual gain control per channel
- * 3-Band EQ with total Kill
- * Fully assignable send and return
- * 12V BNC light socket
- * Booth output
- * Rec. output
- * Balanced XLR and unbalanced RCA outputs
- * 2 BPM counters

Input: Mic	1.5 mV - 2 KOhm balanced
Input: Phono	3 mV - 47 KOhm
Input: Line	150 mV - 27 KOhm
Output: Master	0 dB 1 V/400 Ohm
Output: Record	225 mV - 5Kohm
Equalizer: High	DJ Mic: ± 12 dB
Equalizer: Low	DJ Mic: ± 12 dB
Frequency response	20 Hz-20K Hz ± 2 dB
THD	0.02%
Headphone: Impedance	32 Ohms
Signal to noise ratio	80 dB
Crosstalk	Attenuation: < 16 dB
Output level	20 V - Peak to Peak
Power supply	115/230V - 50/60 Hz - 15 Watt
Dimensions	19" x 4" x 9"
Weight	6.5 Kgs

175.842	MAX 7017 - 5 Channel Mixer - USB - MP3	0.00