



952.084 **PD** Power Dynamics
Professional Audio

PPA502 100V Mixer-Amplifier 50W 2 Zones

The PPA502 is a 100V amplifier with 4/8 ohms, 70V and 100V outputs characterized by easy use, excellent performance and reliability and is therefore particularly suitable for a wide range of small and medium-sized installations. This range of amplifiers is equipped with a multimedia player (USB / SD ports and BT) for MP3 playback. It is also equipped with an equalizer (on the mp3 player), 2 microphone inputs, an auxiliary input and an external 12V connector too. The PPA502 is perfect for commercial environments which require complete control over 2 areas/rooms.

Output power:RMS : 50W
 Impedance : 100V, 70V, 8ohm
 Frequency Response : 50Hz - 18.000Hz
 Signal-to-noise ratio:Line : >80dB
 Signal-to-noise ratio:Mic : >72dB
 Power Supply : 100-240VAC 50/60Hz
 Weight (kg) : 3,40
 Accessories : Power Cable, Remote control

- 50W PA amplifier with 2-zones
- 2-Channel output, volume controllable per channel (6 steps)
- MP3 player with USB and SD slot
- BT receiver for Audio streaming
- Built-in Equalizer on MP3 player
- IR-remote control
- 100V/70V or 4/8 Ohm
- Bass, Treble and Master Volume control
- 2 Microphone-/line inputs (6.3mm Jack)
- 2 stereo line inputs (RCA)
- Stereo RCA Line output
- Telephone input
- 220V mains or 12V for flexible operation