



## PRM606 6-ZONE MATRIX-AMPLIFIER

- 100V matrix amplifier with 6 independent output zones
- 6x 60W Class D power section
- BT receiver for audio streaming
- MP3 player with USB port and SD slot
- LCD control panel with ID3 tag
- 3x mic/line inputs Combi 6.3mm Jack/XLR, 1x RCA line input and 1x RCA line output
- XLR microphone inputs with switchable phantom power (24V) and VOX priority
- 100V or 4/8 Ohm speaker output
- Zone outputs: 6x Line (RCA Mono)
- Zone outputs: 6x Speaker Terminal (100V / 4Ohm / 8Ohm / Com)
- Bass and treble controls
- Chime with level control
- 19" rack mountable (2U)
- Emergency operation by 24V battery (not supplied)
- Protections: Overheat, short circuit and power on delay
- Emergency mute input
- Including remote control



**952.161** CARTON 1 PALLET 30

|                               |                    |
|-------------------------------|--------------------|
| <b>Output power: RMS</b>      | 360W               |
| <b>Impedance</b>              | 100V, 4 Ohm, 8 Ohm |
| <b>Frequency response</b>     | 100HZ - 24.000HZ   |
| <b>Power supply</b>           | 220-240VAC 50HZ    |
| <b>Power consumption</b>      | 2A                 |
| <b>Dimensions (L x W x H)</b> | 390 x 483 x 95mm   |
| <b>Weight</b>                 | 11,85kg            |