



150.587

BBP60 Uplighter Set, 6 pieces in Flightcase with Charger

A complete kit of 6 pieces BBP60 uplighters in a flightcase with built-in charging station. Each BBP60 has a 25Ah battery that will last over 10 hours on a single charging cycle. Once the gig is over, you can simply drop the fixtures back in the charging case and have them charged overnight. Each fixture has a special charging connector on the bottom which connects directly to the flightcase. Simply connect the flightcase with a power outlet and you're done. This set is delivered including a wireless-DMX transmitter to go fully wireless without the need of any extra products. Each set is supplied as 6 uplighters in a built-to-fit flightcase.

Beam angle	15°
No. of colours	RGBWA-UV
No. of LEDs	9x 12W
DMX channels	6 or 10
IP rating	IP20
Power supply	100~240Vac / 60-50Hz
Battery	Lithium 12V / 25Ah
Consumption	90W
Dimensions	670 x 550 x 450mm
Dimensions:Effect	180 x 204 x 220mm
Weight	50kg
Weight:Effect	4.5kg

- 9x 12W 6-1 RGBWA-UV LED
- 6 or 10 DMX channels
- DMX and Stand-alone mode
- Master/slave synchronization
- Sound activated with adjustable sensitivity
- Auto mode
- Beam angle 15°
- 0-100% Electronic Dimmer
- Strobe: 0-24Hz
- DMX in/output via 3-pin XLR
- Each Uplighter contains a Built-in Wireless DMX receiver
- One Wireless Transmitter included in the Set
- Each Uplighter contains a Lithium Battery pack
- Flightcase with Built-in Charger for quick and easy charging
- Powerconnector input