



## **CITRONIC CQ231 2 x 31-BAND EQUALIZER**

Citronic CQ231 2 x 32-band equalizer fitted with balanced XLR/6.35mm in-/output connectors. Numerous controls allow tailor-made adjustment to any venue. Easy to override via the bypass switch.

- 2x 32-band graphic equalizer
- Constant Q
- Low cut filter <40 Hz
- Ultra low noise SMT technology
- Balanced and unbalanced XLR/Jack in- and outputs
- 2x 4 LED VU-meters

Equalizer	+/- 12dB
Frequency response	20 - 20.000 Hz
THD	<0.01%
Signal to noise ratio	>85dB
Input impedance:Balanced	40 kOhm
Input impedance:Unbalanced	20 kOhm
Output impedance:Balanced	102 Ohm
Output impedance:Unbalanced	51 Ohm
Power supply	115/230Vac, 50/60Hz
Dimensions	482 x 120 x 90mm (19inch x 2HE)
Weight	3.1 Kg