





PDM-M804 8-Channel Music Mixer

A full size music mixer with 8 channels. Comes standard with built-in BT receiver and 24-bit Multi-FX processor with 16 presets. Ideal for usage in small to medium sized studio's and recording setups.

Frequency response	10Hz -45kHz (±3dB)
THD	
DSP Resolution	24-bit
Type of effects	Hall, Room, Reverb delay, Delay, Echo
Presets	16
Signal to noise ratio	>112dB
Output level	+/- 1V
Input:Line	+/- 150mV
Input:Mic	+/- 1.5mV
Power supply	100-240VAC / 50-60Hz
Dimensions	290 x 370 x 80cm
Weight	3.2kg

- 8 Balanced mono microphone-/line input (Combi XLR/Jack)
- +48V phantom power
- Multi-FX processor with 16 presets
- Hi, Mid and Low control for each channel
- Adjustable FX, Pan, Trim per channel
- Adjustable headphone output
- Stereo balanced main outputs (6.3mm Jack)
- Separate control room and headphones outputs
- Built-in USB player with digital display
- BT-receiver for audio streaming
- LED VU meter and Peak LED's