



**PD** Power Dynamics 172.624  
Professional Audio

## PDM-S1204 12-Channel Professional Analog Mixer

A 12 channel professional mixer with built-in USB player and BT receiver. Perfect for use on live stage setups, houses of worship or other multi-input venues

<b>Frequency response</b>	10Hz -45kHz ( $\pm 3$ dB)
<b>THD</b>	
<b>DSP Resolution</b>	24-bit
<b>Type of effects</b>	Hall, Room, Chapel, Plate, Spring, Gated rev, Reverse, Early refl, Ambience, Stadium, Delay, Echo, Gate, Chorus, Flanger, Phaser, Pitch, Reverb, Leslie, Flang, Ping pong delay
<b>Presets</b>	256
<b>Signal to noise ratio</b>	>112dB
<b>Output level</b>	+/- 1V
<b>Input:Line</b>	+/- 150mV
<b>Input: Mic</b>	+/- 1.5mV
<b>Power supply</b>	100-240VAC / 50-60Hz
<b>Dimensions</b>	335 x 410 x 95mm
<b>Weight</b>	4.3kg

- 6 Balanced mono microphone inputs (XLR)
- 4 Balanced mono line inputs (6.3mm Jack)
- 4 Balanced stereo line inputs (6.3mm Jack)
- +48V phantom power
- Stereo line input (RCA)
- 75Hz Low cut filter channel 1-4
- Multi-FX processor with 256 presets
- Solo switch per channel (PFL)
- On/off switch per channel
- Hi, Mid and Low control for each channel
- FX inserts on each channel
- Aux send per channel
- Adjustable Pan per channel
- 9-band Equalizer
- Stereo balanced main outputs (XLR + 6.3mm Jack)
- Separate control room, headphones and stereo rec outputs
- Built-in USB player with digital display
- BT-receiver for audio streaming
- LED VU meter and Peak LED's
- Supplied with telephone holder