



**PD** Power Dynamics 172.750  
Professional Audio

## PDZM700 6 Channel Installation Mixer USB 4 zones

The PDZM700 is a 6-channel quality DJ mixer with 4 zones. The 3-band equalizer on each channel ensures a warm and musical sound. Any of the 6 channels can be freely routed to any of the 4 stereo zone outputs. The Cue mixer provides a switch between pre-fade listen on the channels and listen to the master volume in the headphones. The separated microphone channel with equalizer is ideal for presentation or karaoke. The PDZM700 is suitable for bars, club installation, restaurants etcetera..

<b>Frequency response</b>	15Hz - 30kHz
<b>THD</b>	
<b>Equalizer</b>	-30dB / +6dB
<b>Signal to noise ratio</b>	>110dB
<b>Power supply</b>	230VAC / 50Hz
<b>Dimensions</b>	178 x 482 x 100mm (19" x 4 HE)
<b>Weight</b>	3.8kg

- Inputs: 11 stereo line sources (RCA) and 3 microphone (6.3mm Jack)
- Outputs: Zone 1 and balanced master (XLR), zone 2 and zone 3 (RCA)
- Multiple zones assignable per channel
- Separate output volume for each zone
- 2 Built-in USB audio interfaces
- Pre-fade listen per channel
- 6.3mm Headphone output with CUE mix
- 3-band EQ on each channel
- 19" Rack mountable