



## Power Dynamics PBA120 100V Amplifier 120W

This amplifier with excellent performance and reliability is particularly suitable for a wide range of small and medium-sized installations. The amplifier is equipped with USB / SD ports for MP3 playback and has an MP3 control panel. It is equipped with a built-in equalizer, 3 microphone inputs and 2 stereo line inputs. Speaker outputs have options for 4, 8 and 16 ohms as well as 70V and 100V

Power rms	120W
Tappings	4 / 8 / 16 Ohms 70V / 100V
Frequency response	50Hz - 18kHz
Signal to noise ratio	>75dB
Input sensitivity:Line	-16dB
Input sensitivity:Mic	-50dB
Power supply	220-240VAC / 50-60Hz
Dimensions	230 x 320 x 95mm
Weight	5.1kg

- 120W PA amplifier
- MP3 player with USB and SD slot
- BT receiver for Audio streaming
- Built-in Equalizer with presets
- IR-remote control
- 100V / 70V or 16, 8, 4 Ohm
- Bass and Treble control
- Balanced Microphone input with priority
- 2 Microphone-/line inputs (6.3mm Jack)
- 2 stereo line inputs (RCA)
- Stereo RCA Line output
- Telephone input
- MOH output